

HTTP Commands

HTTP URL format

Open door via HTTP command

<https://username:password@deviceIP/fcgi/OpenDoor?action=OpenDoor&DoorNum=1>

Example:

<https://admin:Admin1234@10.1.10.109/fcgi/OpenDoor?action=OpenDoor&DoorNum=1>

Change the number at the end to open certain relays.

- 1 = Relay A
- 2 = Relay B
- 3 = Relay C

HTTP Open Relay: Gate to Monitor

Gate will be an **E18C**

Monitor will be an **S567**

Goal: Have a particular relay in the Gate Intercom when triggered, sends an HTTP command to trigger the relay in the Monitor.

- ❖ Log into the S67
- ❖ Navigate to Device > Relay
- ❖ Enable Open via HTTP and enter a Username and Password
- ❖ Note the IP address of the S567.
- ❖ Create a HTTP URL using the following Template:

<https://username:password@deviceIP/fcgi/OpenDoor?action=OpenDoor&DoorNum=1>

Remember to specify what Relay to activate

- 1 = Relay A
 - 2 = Relay B
-
- ❖ Log into the E18C
 - ❖ Navigate to Access Control > Relay
 - ❖ Enable Open Via HTTP

- ❖ Navigate to Settings > Action URL
- ❖ Paste the HTTP URL in the relay you want to fire Relay B triggered or Relay A triggered
- ❖ Submit